



BE-12xxCx (Coax-con for BE-1806i & BE6060CV)

BE-1204Cx - 4Ch | BE-1208Cx - 8Ch | BE-12164Cx - 16Ch |



- Data Cable not required from Camera to connect RS485
- Save data Cable cost, carry Data over the same Coaxial video cable.
- Latest **Coax-Con** (Coaxial Connect) technology to connect 4 Ch, 8Ch & 16Ch Speed Dome Cameras with just over Coaxial Cables.
- Improves signal transportation quality (450m max).
- Simple updation of any standard Dome/IR camera to a Speed Dome Camera without any additional cable/s.

Specifications:

Signal System	PAL
Video Input	4/8/16 Ch
Video Output	4/8/16 Ch
Communication interface	RS485, BNC (Coax-con)
Communication protocol	Pelco D
Baud Rate	1200,2400,4800,9600
Operation	key
Display	3bit LED
Supply Voltage	DC 12V
Work Temperature	-20°C ~ +50°C
Dimension (mm) /Weight (g)	325×180×55mm

