

PIR LIGHT SWITCHS

A-ES1



Pir Motion Sensor For Light Control With Manual Override

A-ES1 sensor switch can detect the infrared Rays released by human body motion within the Detection area, then start the load-light automatically. This unit is suitable for outdoor use.

This PIR Sensor has an extra feature of manual override. A-ES1 has a longer detection range and wider angle, it is better for security use.

Many customers like to install the A-ES1 in the garden, because it has an overridden function. A-ES1 can load higher watts, so the sensor is suitable for outdoor.

SPECIFICATIONS

Power Requirement	: 230V AC 50Hz
Lighting Load	: Max. 1000W incandescent bulb or Max. 300W fluorescent lamp
Detection Angle	: Max. 180°
Detection Distance	: Max. 12 meters
Time Adjustment	: From 10±5 seconds to 6±1 minutes adjustable
Lux Adjustment	: From daytime to darkness adjustable
Protection Class	: IP44

APPLICATION AREA

Car Park , Corridor, Dining Area, Individual Cabins, Large Cabins, Lift Lobby, Lifts, Living Room, Lobbies, Meeting Rooms, Pantry, Reception Areas, Rest Room, Small Offices, Stairways, Stores, Veranda.