

PIR LIGHT SWITCHS

A-ES11



A-ES11 PIR Motion Sensor with Floodlight.

Halogen Lamps A-ES11 150W watt and Halogen Lamps A-ES11 500W watt.

The infrared induced lamp has an infrared detector with it. When the thermal body moving in the darkness the detector will light the lamp automatically and turn off after a period of time set in advance.

PIR Motion Sensor with Floodlight, Day and Night mode, Time adjustment, Selectable sensitivity of the detector.

SPECIFICATIONS

Power Source	: AC 220/240, 50Hz
Max Lighting load	: 150W/500W (Halogen tube)
Detection angle	: up to 120 °
Detection range	: up to 14Meters<
Time adjustment	: (10 ± 5) sec. to (4 ± 1) min
Warm uptime	: about 1 min
Mounting Height	:1.8 Meters to 2.4 Meters

APPLICATION AREA

Store Room, Parking Lot, Near Gate, Basements, Multi Apartment Complexes, Garage.